

Constant/value	Description
<b>VK_LBUTTON</b> <b>0x01</b>	Left mouse button
<b>VK_RBUTTON</b> <b>0x02</b>	Right mouse button
<b>VK_CANCEL</b> <b>0x03</b>	Control-break processing
<b>VK_MBUTTON</b> <b>0x04</b>	Middle mouse button (three-button mouse)
<b>VK_XBUTTON1</b> <b>0x05</b>	X1 mouse button
<b>VK_XBUTTON2</b> <b>0x06</b>	X2 mouse button
- <b>0x07</b>	Undefined
<b>VK_BACK</b> <b>0x08</b>	BACKSPACE key
<b>VK_TAB</b> <b>0x09</b>	TAB key
- <b>0x0A-0B</b>	Reserved
<b>VK_CLEAR</b> <b>0x0C</b>	CLEAR key
<b>VK_RETURN</b> <b>0x0D</b>	ENTER key
- <b>0x0E-0F</b>	Undefined
<b>VK_SHIFT</b> <b>0x10</b>	SHIFT key
<b>VK_CONTROL</b> <b>0x11</b>	CTRL key
<b>VK_MENU</b> <b>0x12</b>	ALT key
<b>VK_PAUSE</b> <b>0x13</b>	PAUSE key
<b>VK_CAPITAL</b> <b>0x14</b>	CAPS LOCK key
<b>VK_KANA</b> <b>0x15</b>	IME Kana mode
<b>VK_HANGUEL</b> <b>0x15</b>	IME Hanguel mode (maintained for compatibility; use VK_HANGUL)
<b>VK_HANGUL</b> <b>0x15</b>	IME Hangul mode

- 0x16	Undefined
VK_JUNJA 0x17	IME Junja mode
VK_FINAL 0x18	IME final mode
VK_HANJA 0x19	IME Hanja mode
VK_KANJI 0x19	IME Kanji mode
- 0x1A	Undefined
VK_ESCAPE 0x1B	ESC key
VK_CONVERT 0x1C	IME convert
VK_NONCONVERT 0x1D	IME nonconvert
VK_ACCEPT 0x1E	IME accept
VK_MODECHANGE 0x1F	IME mode change request
VK_SPACE 0x20	SPACEBAR
VK_PRIOR 0x21	PAGE UP key
VK_NEXT 0x22	PAGE DOWN key
VK_END 0x23	END key
VK_HOME 0x24	HOME key
VK_LEFT 0x25	LEFT ARROW key
VK_UP 0x26	UP ARROW key
VK_RIGHT 0x27	RIGHT ARROW key
VK_DOWN 0x28	DOWN ARROW key
VK_SELECT 0x29	SELECT key
VK_PRINT 0x2A	PRINT key

<b>VK_EXECUTE</b> <b>0x2B</b>	EXECUTE key
<b>VK_SNAPSHOT</b> <b>0x2C</b>	PRINT SCREEN key
<b>VK_INSERT</b> <b>0x2D</b>	INS key
<b>VK_DELETE</b> <b>0x2E</b>	DEL key
<b>VK_HELP</b> <b>0x2F</b>	HELP key
<b>0x30</b>	0 key
<b>0x31</b>	1 key
<b>0x32</b>	2 key
<b>0x33</b>	3 key
<b>0x34</b>	4 key
<b>0x35</b>	5 key
<b>0x36</b>	6 key
<b>0x37</b>	7 key
<b>0x38</b>	8 key
<b>0x39</b>	9 key
<b>-</b> <b>0x3A-40</b>	Undefined
<b>0x41</b>	A key
<b>0x42</b>	B key
<b>0x43</b>	C key
<b>0x44</b>	D key
<b>0x45</b>	E key
<b>0x46</b>	F key

<b>0x47</b>	G key
<b>0x48</b>	H key
<b>0x49</b>	I key
<b>0x4A</b>	J key
<b>0x4B</b>	K key
<b>0x4C</b>	L key
<b>0x4D</b>	M key
<b>0x4E</b>	N key
<b>0x4F</b>	O key
<b>0x50</b>	P key
<b>0x51</b>	Q key
<b>0x52</b>	R key
<b>0x53</b>	S key
<b>0x54</b>	T key
<b>0x55</b>	U key
<b>0x56</b>	V key
<b>0x57</b>	W key
<b>0x58</b>	X key
<b>0x59</b>	Y key
<b>0x5A</b>	Z key
<b>VK_LWIN</b> <b>0x5B</b>	Left Windows key (Natural keyboard)
<b>VK_RWIN</b> <b>0x5C</b>	Right Windows key (Natural keyboard)

<b>VK_APPS</b> <b>0x5D</b>	Applications key (Natural keyboard)
<b>_</b> <b>0x5E</b>	Reserved
<b>VK_SLEEP</b> <b>0x5F</b>	Computer Sleep key
<b>VK_NUMPAD0</b> <b>0x60</b>	Numeric keypad 0 key
<b>VK_NUMPAD1</b> <b>0x61</b>	Numeric keypad 1 key
<b>VK_NUMPAD2</b> <b>0x62</b>	Numeric keypad 2 key
<b>VK_NUMPAD3</b> <b>0x63</b>	Numeric keypad 3 key
<b>VK_NUMPAD4</b> <b>0x64</b>	Numeric keypad 4 key
<b>VK_NUMPAD5</b> <b>0x65</b>	Numeric keypad 5 key
<b>VK_NUMPAD6</b> <b>0x66</b>	Numeric keypad 6 key
<b>VK_NUMPAD7</b> <b>0x67</b>	Numeric keypad 7 key
<b>VK_NUMPAD8</b> <b>0x68</b>	Numeric keypad 8 key
<b>VK_NUMPAD9</b> <b>0x69</b>	Numeric keypad 9 key
<b>VK_MULTIPLY</b> <b>0x6A</b>	Multiply key
<b>VK_ADD</b> <b>0x6B</b>	Add key
<b>VK_SEPARATOR</b> <b>0x6C</b>	Separator key
<b>VK_SUBTRACT</b> <b>0x6D</b>	Subtract key
<b>VK_DECIMAL</b> <b>0x6E</b>	Decimal key
<b>VK_DIVIDE</b> <b>0x6F</b>	Divide key
<b>VK_F1</b> <b>0x70</b>	F1 key
<b>VK_F2</b> <b>0x71</b>	F2 key
<b>VK_F3</b> <b>0x72</b>	F3 key

<b>VK_F4</b> <b>0x73</b>	F4 key
<b>VK_F5</b> <b>0x74</b>	F5 key
<b>VK_F6</b> <b>0x75</b>	F6 key
<b>VK_F7</b> <b>0x76</b>	F7 key
<b>VK_F8</b> <b>0x77</b>	F8 key
<b>VK_F9</b> <b>0x78</b>	F9 key
<b>VK_F10</b> <b>0x79</b>	F10 key
<b>VK_F11</b> <b>0x7A</b>	F11 key
<b>VK_F12</b> <b>0x7B</b>	F12 key
<b>VK_F13</b> <b>0x7C</b>	F13 key
<b>VK_F14</b> <b>0x7D</b>	F14 key
<b>VK_F15</b> <b>0x7E</b>	F15 key
<b>VK_F16</b> <b>0x7F</b>	F16 key
<b>VK_F17</b> <b>0x80</b>	F17 key
<b>VK_F18</b> <b>0x81</b>	F18 key
<b>VK_F19</b> <b>0x82</b>	F19 key
<b>VK_F20</b> <b>0x83</b>	F20 key
<b>VK_F21</b> <b>0x84</b>	F21 key
<b>VK_F22</b> <b>0x85</b>	F22 key
<b>VK_F23</b> <b>0x86</b>	F23 key
<b>VK_F24</b> <b>0x87</b>	F24 key
<b>-</b> <b>0x88-8F</b>	Unassigned

<b>VK_NUMLOCK</b> <b>0x90</b>	NUM LOCK key
<b>VK_SCROLL</b> <b>0x91</b>	SCROLL LOCK key
<b>0x92-96</b>	OEM specific
<b>-</b> <b>0x97-9F</b>	Unassigned
<b>VK_LSHIFT</b> <b>0xA0</b>	Left SHIFT key
<b>VK_RSHIFT</b> <b>0xA1</b>	Right SHIFT key
<b>VK_LCONTROL</b> <b>0xA2</b>	Left CONTROL key
<b>VK_RCONTROL</b> <b>0xA3</b>	Right CONTROL key
<b>VK_LMENU</b> <b>0xA4</b>	Left MENU key
<b>VK_RMENU</b> <b>0xA5</b>	Right MENU key
<b>VK_BROWSER_BACK</b> <b>0xA6</b>	Browser Back key
<b>VK_BROWSER_FORWARD</b> <b>0xA7</b>	Browser Forward key
<b>VK_BROWSER_REFRESH</b> <b>0xA8</b>	Browser Refresh key
<b>VK_BROWSER_STOP</b> <b>0xA9</b>	Browser Stop key
<b>VK_BROWSER_SEARCH</b> <b>0xAA</b>	Browser Search key
<b>VK_BROWSER_FAVORITES</b> <b>0xAB</b>	Browser Favorites key
<b>VK_BROWSER_HOME</b> <b>0xAC</b>	Browser Start and Home key
<b>VK_VOLUME_MUTE</b> <b>0xAD</b>	Volume Mute key
<b>VK_VOLUME_DOWN</b> <b>0xAE</b>	Volume Down key
<b>VK_VOLUME_UP</b> <b>0xAF</b>	Volume Up key
<b>VK_MEDIA_NEXT_TRACK</b> <b>0xB0</b>	Next Track key
<b>VK_MEDIA_PREV_TRACK</b> <b>0xB1</b>	Previous Track key

<b>VK_MEDIA_STOP</b> <b>0xB2</b>	Stop Media key
<b>VK_MEDIA_PLAY_PAUSE</b> <b>0xB3</b>	Play/Pause Media key
<b>VK_LAUNCH_MAIL</b> <b>0xB4</b>	Start Mail key
<b>VK_LAUNCH_MEDIA_SELECT</b> <b>0xB5</b>	Select Media key
<b>VK_LAUNCH_APP1</b> <b>0xB6</b>	Start Application 1 key
<b>VK_LAUNCH_APP2</b> <b>0xB7</b>	Start Application 2 key
- <b>0xB8-B9</b>	Reserved
<b>VK_OEM_1</b> <b>0xBA</b>	Used for miscellaneous characters; it can vary by keyboard. For the US standard keyboard, the ';' key
<b>VK_OEM_PLUS</b> <b>0xBB</b>	For any country/region, the '+' key
<b>VK_OEM_COMMA</b> <b>0xBC</b>	For any country/region, the ',' key
<b>VK_OEM_MINUS</b> <b>0xBD</b>	For any country/region, the '-' key
<b>VK_OEM_PERIOD</b> <b>0xBE</b>	For any country/region, the '.' key
<b>VK_OEM_2</b> <b>0xBF</b>	Used for miscellaneous characters; it can vary by keyboard. For the US standard keyboard, the '/' key
<b>VK_OEM_3</b> <b>0xC0</b>	Used for miscellaneous characters; it can vary by keyboard. For the US standard keyboard, the '~' key
- <b>0xC1-D7</b>	Reserved
- <b>0xD8-DA</b>	Unassigned
<b>VK_OEM_4</b> <b>0xDB</b>	Used for miscellaneous characters; it can vary by keyboard. For the US standard keyboard, the '[' key
<b>VK_OEM_5</b> <b>0xDC</b>	Used for miscellaneous characters; it can vary by keyboard. For the US standard keyboard, the '\ ' key
<b>VK_OEM_6</b> <b>0xDD</b>	Used for miscellaneous characters; it can vary by keyboard. For the US standard keyboard, the ']' key
<b>VK_OEM_7</b> <b>0xDE</b>	Used for miscellaneous characters; it can vary by keyboard. For the US standard keyboard, the 'single-quote/double-quote' key
<b>VK_OEM_8</b> <b>0xDF</b>	Used for miscellaneous characters; it can vary by keyboard.
- <b>0xE0</b>	Reserved



<b>0xE1</b>	OEM specific
<b>VK_OEM_102</b> <b>0xE2</b>	Either the angle bracket key or the backslash key on the RT 102-key keyboard
<b>0xE3-E4</b>	OEM specific
<b>VK_PROCESSKEY</b> <b>0xE5</b>	IME PROCESS key
<b>0xE6</b>	OEM specific
<b>VK_PACKET</b> <b>0xE7</b>	key is the low word of a 32-bit Virtual Key value used for non-keyboard input methods. For more information, see Remark in <a href="#">KEYBDINPUT</a> , <a href="#">SendInput</a> , <a href="#">WM_KEYDOWN</a> , and <a href="#">WM_KEYUP</a>
- <b>0xE8</b>	Unassigned
<b>0xE9-F5</b>	OEM specific
<b>VK_ATTN</b> <b>0xF6</b>	Attn key
<b>VK_CRSEL</b> <b>0xF7</b>	CrSel key
<b>VK_EXSEL</b> <b>0xF8</b>	ExSel key
<b>VK_EREOF</b> <b>0xF9</b>	Erase EOF key
<b>VK_PLAY</b> <b>0xFA</b>	Play key
<b>VK_ZOOM</b> <b>0xFB</b>	Zoom key
<b>VK_NONAME</b> <b>0xFC</b>	Reserved
<b>VK_PA1</b> <b>0xFD</b>	PA1 key
<b>VK_OEM_CLEAR</b> <b>0xFE</b>	Clear key